

DATA SHEET

CISCO ISDN BRI S/T WIC FOR THE CISCO 1700, 1800, 2600, 2800, 3600, 3700, AND 3800 SERIES

Offering a single ISDN BRI S/T interface, this WIC may require an external Network Termination 1 (NT1), depending on the region of the world. The WIC inserts into a mixed-media network module or directly into the WIC slot on the Cisco 1600, 1700, 1800, 2600, 2800, 3600, 3700, 3800 Series chassis. The ability to add BRI connectivity through a WIC enables administrators to maximize valuable slot space while providing additional connectivity options, such as Ethernet, on the same module.

Figure 1. Cisco WIC 1B-S/T-V3 WAN Interface Card



FEATURES

- One ISDN BRI port (S/T interface, requires external NT1)
- Utilizes an RJ-45 connector
- Supported Onboard, NM-1FE2W-V2, NM-1FE1R2W, NM-2FE2W-V2 and NM-2W

BENEFITS OF AN INTEGRATED, FULLY MANAGED SOLUTION

The network modules provide various port densities to meet customer requirements at various price points. The optional, integrated NT1 lets customers consolidate customer premises equipment (CPE) to provide multifunction dial access server, router, and other capabilities within the Cisco routers in power-branch-office environments.

The WAN-interface-card (WIC) option offers a single ISDN BRI port (with optional NT1). The WIC-1B-S/T-V3 inserts into a mixed-media network module (part number NM-1FE2W-V2, NM-2FE2W-V2, NM-1FE1R2W or NM-2W) or is supported on the Cisco 1700 Series, Cisco 1800 Series, Cisco 2600XM Series, Cisco 2800 Series, Cisco 3700 Series and Cisco 3800 Series routers. It provides a cost-effective ISDN router with the following benefits of integration:

- Fewer devices and cables to deploy and manage
- Remote and local configuration, monitoring, and troubleshooting via the Cisco IOS® Software CLI and Simple Network Management Protocol (SNMP)
- Flexibility and investment protection
- Single-vendor support
- Enhanced reliability

- Physical space savings

The ability to add BRI connectivity via a WIC enables administrators to maximize valuable slot space while providing additional connectivity options on the same module such as Fast Ethernet.

FLEXIBILITY AND INVESTMENT PROTECTION

The Cisco 1 port BRI-S/T WIC extends the Cisco commitment to providing customers with maximum flexibility and investment protection through modular WICs that are supported on award-winning router platforms. When WAN bandwidth requirements or service provider pricing change, users can easily change WAN services either by changing the software configuration or replacing the WIC. Because the same card can be used on Cisco 1600, 1700, 1800, 2600, 2800, 3700 or 3800 series router platforms, the number of stocking units can be reduced, and the WIC can be redeployed from one platform to another.

ENHANCED RELIABILITY

An integrated solution has fewer components; hence, fewer points of failure (for example, one less power supply and fewer cables). This leads to enhanced reliability.

CONSISTENCY WITH WIC-1B-S/T

The Cisco WIC-1B-S/T-V3 offers all of the features of the Cisco WIC-1B-S/T and can be smoothly deployed without requiring any additional learning.

WIC-1B-S/T	WIC-1B-S/T-V3
One ISDN BRI port (S/T interface, requires external NT1)	One ISDN BRI port (S/T interface, requires external NT1)
RJ-45 connector	RJ-45 connector
Supported on Cisco 1600, 1700, 2600, 3600, and series	Supported on Cisco 1700, 1800, 2600, 2800, 3660, 3700 and 3800 series (see tables below)
Cannot be used with Cisco 1603 or 1604 base units	Cannot be used with Cisco 1603 or 1604 base units
Does not support hot swapping; however, no hardware damage will occur if it is swapped while power is on	Does not support hot swapping; however, no hardware damage will occur if it is swapped while power is on
Can go into slot W0 or W1 of the 1E2W, 2E2W, and 1E1R2W network modules	Does not support the 1E2W, 2E2W, and 1E1R2W, NM-1FE2W, NM-2FE2W network modules
Supported in NM-1FE1R2W, NM-1FE2W, NM-2FE2W, NM-1FE2W-V2, NM-2FE-2W-V2, and NM-2W	Supported Onboard, NM-1FE2W-V2, NM-1FE1R2W, NM-2FE2W-V2 and NM-2W

Note: The Cisco IOS Software releases provided are typically the minimum version required to support the platform, module, or feature in question. Use the Software Advisor to choose appropriate software for your network device: match software features to Cisco IOS and Cisco Catalyst® Operating System (Catalyst OS) releases, compare Cisco IOS releases, or find out which software releases support your hardware. The Software Advisor and other tools are available in TAC Tools for Access-Dial Technologies.

CISCO IOS SOFTWARE RELEASE

Platform	Minimum Release
Cisco 1601(R), 1602(R), and 1605-R	Not Supported
Cisco 1603, 1603-R, 1604 and 1604-R	Not Supported
Cisco 1720, 1721, 1751, 1760	First Supported in 12.3(10)
Cisco 1750	Not Supported
Cisco 2600 and 2600XM	First Supported in 12.3(10)
Cisco 3620 and 3640	Not Supported
Cisco 3660	First Supported in 12.3(10)
Cisco 3700	First Supported in 12.3(10)
Cisco 1800 and 2800	First Supported in 12.3(8)T
Cisco 3800	First Supported in 12.3(11)T

Note: The Cisco IOS Software releases provided are typically the minimum version required to support the platform, module, or feature in question. Use the Software Advisor to choose appropriate software for your network device: match software features to Cisco IOS and Cisco Catalyst® Operating System (Catalyst OS) releases, compare Cisco IOS releases, or find out which software releases support your hardware. The Software Advisor and other tools are available in TAC Tools for Access-Dial Technologies.

CARRIER MODULE SUPPORTED

Platform	Carrier Module Supported
Cisco 1601(R), 1602(R), and 1605-R	Not Supported
Cisco 1603, 1603-R, 1604 and 1604-R	Not Supported
Cisco 1720, 1721, 1751 ,1760	Not Supported
Cisco 1750	Not Supported
Cisco 2600 and 2600XM	Onboard. NM-2W
Cisco 3620 and 3640	Not Supported
Cisco 3660	NM-1FE2W-V2, NM-1FE1R2W, NM-2FE2W-V2 and NM-2W
Cisco 3700	NM-1FE2W-V2, NM-1FE1R2W, NM-2FE2W-V2 and NM-2W
Cisco 1800 and 2800	Onboard
Cisco 3800	Onboard, NM-1FE2W-V2, NM-1FE1R2W, NM-2FE2W-V2 and NM-2W

Note: The Cisco IOS Software releases provided are typically the minimum version required to support the platform, module, or feature in question. Use the Software Advisor to choose appropriate software for your network device: match software features to Cisco IOS and Cisco

Catalyst® Operating System (Catalyst OS) releases, compare Cisco IOS releases, or find out which software releases support your hardware. The Software Advisor and other tools are available in TAC Tools for Access-Dial Technologies.

SPECIFICATIONS

Product Number	Description
WIC-1B-S/T-V3	1-Port ISDN WAN Interface Card (dial and leased line)

SAFETY, EMC, TELECOM, NETWORK HOMOLOGATION, POWER REQUIREMENTS

When installed in a Cisco 2600/3600/3700 Router, the Cisco WIC-1ADSL does not change the standards (safety, EMC, telecom, network homologation and power) of the router itself. For more information, see the platform specific data sheets at the following URLs:

- Cisco 2600/2600XM/2691 Series: http://www.cisco.com/en/US/prod/collateral/routers/ps259/product_data_sheet0900aecd800fa5be.html
- Cisco 3600 Series: http://www.cisco.com/en/US/products/hw/routers/ps274/products_data_sheets_list.html
- Cisco 3700 Series: http://www.cisco.com/en/US/prod/collateral/routers/ps282/product_data_sheet09186a008009203f.html

Dimensions and Weight

- Dimensions (H x W x D)
 - 1.55 x 7.10 x 7.2 in. 1.55 x 7.10 x 7.2 in. .75 x 3.08x 4.38 in.
- Weight
 - 2 lb max 2 lb max 2.4 oz

Diagnostics

- LEDs
 - Network module status indicator, status LEDs for each B Channel and NTI
- Environmental conditions
 - Operating temperature 32 to 104°F (0 to 40°C),
 - Nonoperating temperature 13 to 158°F (–25 to 70°C)
- Relative humidity
 - to 95% noncondensing
- Cabling
 - RJ-45 connectors

**Corporate Headquarters**

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
www.cisco.com
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 526-4100

European Headquarters

Cisco Systems International BV
Haarlerbergpark
Haarlerbergweg 13-19
1101 CH Amsterdam
The Netherlands
www-europe.cisco.com
Tel: 31 0 20 357 1000
Fax: 31 0 20 357 1100

Americas Headquarters

Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
www.cisco.com
Tel: 408 526-7660
Fax: 408 527-0883

Asia Pacific Headquarters

Cisco Systems, Inc.
168 Robinson Road
#28-01 Capital Tower
Singapore 068912
www.cisco.com
Tel: +65 6317 7777
Fax: +65 6317 7799

Cisco Systems has more than 200 offices in the following countries and regions. Addresses, phone numbers, and fax numbers are listed on **the Cisco Website at www.cisco.com/go/offices.**

Argentina • Australia • Austria • Belgium • Brazil • Bulgaria • Canada • Chile • China PRC • Colombia • Costa Rica • Croatia • Cyprus
Czech Republic • Denmark • Dubai, UAE • Finland • France • Germany • Greece • Hong Kong SAR • Hungary • India • Indonesia • Ireland • Israel
Italy • Japan • Korea • Luxembourg • Malaysia • Mexico • The Netherlands • New Zealand • Norway • Peru • Philippines • Poland • Portugal
Puerto Rico • Romania • Russia • Saudi Arabia • Scotland • Singapore • Slovakia • Slovenia • South Africa • Spain • Sweden • Switzerland • Taiwan
Thailand • Turkey • Ukraine • United Kingdom • United States • Venezuela • Vietnam • Zimbabwe

Copyright © 2005 Cisco Systems, Inc. All rights reserved. CCSP, CCVP, the Cisco Square Bridge logo, Follow Me Browsing, and StackWise are trademarks of Cisco Systems, Inc.; Changing the Way We Work, Live, Play, and Learn, and iQuick Study are service marks of Cisco Systems, Inc.; and Access Registrar, Aironet, ASIST, BPX, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Empowering the Internet Generation, Enterprise/Solver, EtherChannel, EtherFast, EtherSwitch, Fast Step, FormShare, GigaDrive, GigaStack, HomeLink, Internet Quotient, IOS, IP/TV, iQ Expertise, the iQ logo, iQ Net Readiness Scorecard, LightStream, Linksys, MeetingPlace, MGX, the Networkers logo, Networking Academy, Network Registrar, Packet, PIX, Post-Routing, Pre-Routing, ProConnect, RateMUX, ScriptShare, SlideCast, SMARTnet, StrataView Plus, TeleRouter, The Fastest Way to Increase Your Internet Quotient, and TransPath are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or Website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0502R) 204184.cb_ETMG_JR_3.08.05_v.1

